

A Purification Scheme and Entanglement Distillations

Hiromichi Nakazato,* Makoto Unoki, and Kazuya Yuasa†
Department of Physics, Waseda University, Tokyo 169-8555, Japan
(Revised: 2008.2.1)

A purification scheme which utilizes the action of repeated measurements on a (part of a total) quantum system is briefly reviewed and is applied to a few simple systems to show how it enables us to extract an entangled state as a target pure state. The scheme is rather simple (e.g., we need not prepare a specific initial state) and is shown to have wide applicability and flexibility, and is able to accomplish both the maximal fidelity and non-vanishing yield.

PACS numbers: 03.65.Xp, 03.67.Mn

I. INTRODUCTION

It is well known that in quantum mechanics, the action of measurement affects the dynamics of the system just measured in an essential way. This has to be contrasted with the situation in classical mechanics, where the effect of measurement can be made as small as one wishes. Typical phenomenon reflecting such a peculiarity in quantum mechanics has been known under the name of “Quantum Zeno Effect (QZE)” [1] and has been extensively studied recently. It states that if a system is frequently measured to confirm that it is in its initial state, the change of the state based on the Hamiltonian of the system is decelerated, or to state differently, the decay of an unstable state is hindered by frequent measurements. It is widely recognized, however, that there is no paradoxical point in such phenomena and the effect is solely understood quantum mechanically [2]. Indeed, the projective measurement is not essential and is just replaced with the generalized spectral decompositions [3], and the effect is due to the peculiar short-time dynamics of quantum systems, known as the “flat derivative” of the survival probability, $\dot{P}(0) = 0$. The effect has also been examined experimentally and the first announcement of its confirmation appeared in an oscillating system [4] and then in a truly unstable system [5]. It is worth while mentioning that Raizen’s group has observed the deviation from the exponential law at short times [6] and even the acceleration of decay when the measurements are not frequent enough [5]. The latter effect is called the “Inverse (or Anti) Zeno Effect (IZE),” which has also been studied and discussed [7]. The QZE (and/or IZE) has still been explored extensively in the hope of realizing a protection scheme for system’s coherence against possible decoherence by this (or its related) mechanism [8].

Here another interesting consequence of the peculiarity of quantum measurement shall be disclosed. We consider a total system that is composed of two (sub)systems A and B and measurements shall be repeatedly performed only on system A at regular intervals. Our interest lies

in the (asymptotic) dynamics of system B, which is indirectly affected by the measurements on A through its interaction with A. It is shown that such indirect measurements can drive system B to a pure state (*purification*), irrespectively of its initial state that is mixed in general [9]. We can say that the effect of measurement is far reaching and profound: It can control even the other parts of the system which are not touched directly. In the following sections, the mechanism of this purification is briefly reviewed (Sec. II) and is applied to a simple qubit system (Sec. III) to show how it works and how it can be optimized. Since the entangled state, which is one of the key elements in quantum technologies like quantum computation, information, teleportation, etc. [10], is a pure state of a compound system, this method is used to extract entangled states [11, 12] in Secs. IV and V. A brief summary is presented in Sec. VI.

II. GENERAL FRAMEWORK OF PURIFICATION THROUGH REPEATED MEASUREMENTS

Let the total system consist of two parts, system A and system B, and the dynamics be described by the total Hamiltonian

$$H = H_A + H_B + H_{int}, \quad (1)$$

where H_{int} stands for the interaction between the two (sub)systems. We initially prepare the system in a product state

$$\rho_0 = |\phi\rangle\langle\phi| \otimes \rho_B(0) \quad (2)$$

at $t = 0$. Such a state can be realized, say, if the system A is found in the state $|\phi\rangle$ after the zeroth measurement. Notice that system B can be in an *arbitrary mixed* state $\rho_B(0)$. We perform measurements on A at regular intervals τ to confirm that it is still in the state $|\phi\rangle$, even though the total system A+B evolves unitarily in terms of the total Hamiltonian H . Since the measurement is performed only on system A, the action of such a (projective, for simplicity) measurement can be conveniently described by the following projection operator

$$\mathcal{O} \equiv |\phi\rangle\langle\phi| \otimes \hat{1}_B. \quad (3)$$

*Electronic address: hiromici@waseda.jp

†Electronic address: yuasa@hep.phys.waseda.ac.jp

Thus the state of system A is set back to $|\phi\rangle$ every after τ , while that of B just evolves dynamically on the basis of the total Hamiltonian H . We repeat the same measurement, represented by (3), N times and collect only those events in which system A has been found in state $|\phi\rangle$ consecutively N times; other events are discarded. The state of system B is then described by the density matrix

$$\rho_B^{(\tau)}(N) = (V_\phi(\tau))^N \rho_B(0) (V_\phi^\dagger(\tau))^N / P^{(\tau)}(N), \quad (4)$$

where

$$V_\phi(\tau) \equiv \langle \phi | e^{-iH\tau} | \phi \rangle \quad (5)$$

is an operator acting on B and

$$\begin{aligned} P^{(\tau)}(N) &= \text{Tr} \left[(\mathcal{O} e^{-iH\tau} \mathcal{O})^N \rho_0 (\mathcal{O} e^{iH\tau} \mathcal{O})^N \right] \\ &= \text{Tr}_B \left[(V_\phi(\tau))^N \rho_B(0) (V_\phi^\dagger(\tau))^N \right] \end{aligned} \quad (6)$$

is the success probability for these events to occur (yield). This normalization factor in (4) reflects the fact that only right outcomes are collected in this process.

In order to examine the asymptotic state of system B, consider the spectral decomposition of the operator $V_\phi(\tau)$, which is not hermitian, $V_\phi(\tau) \neq V_\phi^\dagger(\tau)$. We therefore need to set up both the right- and left-eigenvalue problems

$$V_\phi(\tau) |u_n\rangle = \lambda_n |u_n\rangle, \quad \langle v_n | V_\phi(\tau) = \lambda_n \langle v_n|. \quad (7)$$

The eigenvalue λ_n is complex valued in general, but its absolute value is bounded [12]

$$0 \leq |\lambda_n| \leq 1, \quad (8)$$

which is a reflection of the unitarity of the time evolution operator $e^{-iH\tau}$. These eigenvectors are assumed to form a complete orthonormal set in the following sense

$$\sum_n |u_n\rangle \langle v_n| = \hat{1}_B, \quad \langle v_n | u_m \rangle = \delta_{nm}. \quad (9)$$

Then the operator $V_\phi(\tau)$ itself is expanded in terms of these eigenvectors

$$V_\phi(\tau) = \sum_n \lambda_n |u_n\rangle \langle v_n|. \quad (10)$$

It is now easy to see that the N th power of this operator is expressed as

$$(V_\phi(\tau))^N = \sum_n \lambda_n^N |u_n\rangle \langle v_n| \quad (11)$$

and therefore it is dominated by a single term for large N

$$(V_\phi(\tau))^N \xrightarrow{\text{large } N} \lambda_0^N |u_0\rangle \langle v_0|, \quad (12)$$

when the largest (in magnitude) eigenvalue λ_0 is *discrete, nondegenerate and unique*. If these conditions are satisfied, the density operator of system B is driven to a pure state

$$\rho_B^{(\tau)}(N) \xrightarrow{\text{large } N} |u_0\rangle \langle u_0| / (u_0 | u_0) \quad (13)$$

with the probability

$$P^{(\tau)}(N) \xrightarrow{\text{large } N} |\lambda_0|^{2N} (u_0 | u_0) (v_0 | \rho_B(0) | v_0). \quad (14)$$

The pure state $|u_0\rangle$, which is nothing but the right-eigenvector of the operator $V_\phi(\tau)$ belonging to the largest (in magnitude) eigenvalue λ_0 , is thus distilled in system B. This is the purification scheme proposed in [9].

A few comments are in order. First, the final pure state $|u_0\rangle$ toward which system B is to be driven is dependent on the choice of the state $|\phi\rangle$ on which system A is projected every after measurement, the measurement interval τ and the Hamiltonian H , but does not depend on the initial state of system B at all. In this sense, the purification is accomplished irrespectively of the initial (mixed) state $\rho_B(0)$. Second, as is clear in the above exposition, what is crucial in this purification scheme is the repetition of one and the same measurement (more appropriately, spectral decomposition) and the measurement interval τ need not be very small. It remains to be an adjustable parameter. Third, if we can make other eigenvalues than λ_0 much smaller in magnitude

$$|\lambda_n / \lambda_0| \ll 1 \quad \text{for } n \neq 0, \quad (15)$$

by adjusting parameters, we will need fewer steps (i.e., smaller N) to purify system B.

It is now evident that the purification can be made *optimal*, if the conditions (15) and

$$|\lambda_0| = 1 \quad (16)$$

are satisfied. This condition (16) assures that we can repeat as many measurements as we wish without running the risk of losing the yield (success probability) $P^{(\tau)}(N)$ in order to make the fidelity to the target state $|u_0\rangle$,

$$F^{(\tau)}(N) \equiv \text{Tr}_B \left[\rho_B^{(\tau)}(N) |u_0\rangle \langle u_0| / (u_0 | u_0) \right], \quad (17)$$

higher. Actually, the yield $P^{(\tau)}(N)$ decays like

$$\begin{aligned} P^{(\tau)}(N) &= \sum_{n,m} \lambda_n^N \lambda_m^{*N} (v_n | \rho_B(0) | v_m) (u_m | u_n) \\ &\xrightarrow{\text{large } N} |\lambda_0|^{2N} (u_0 | u_0) (v_0 | \rho_B(0) | v_0) \end{aligned} \quad (18)$$

and the condition (16) can bring us with the non-vanishing yield $(u_0 | u_0) (v_0 | \rho_B(0) | v_0)$ even in the $N \rightarrow \infty$ limit. Therefore the condition (16) makes the two (sometimes not compatible) demands, i.e., *higher fidelity and non-vanishing yield*, achievable, with fewer steps when the condition (15) is met. In this sense, the purification is considered to be optimal.

It would be desirable if an optimal purification can be realized by an appropriate choice of the state $|\phi\rangle$ and/or tuning of the measurement interval τ and parameters in a given system. In the following sections, a few simple systems are examined to show how such optimal purifications are made possible.

III. PURIFICATION OF A QUBIT

As a simplest example, let us consider a total system of interacting two qubits. Systems A and B are represented by two qubits A and B, respectively, and their two levels can be described as the two degrees of freedom of spin-1/2 particle. We measure qubit A at regular intervals τ and examine the state of qubit B, which is in interaction with A. The measurement is conveniently parameterized as that of a spin-1/2 particle along a particular direction $\mathbf{n}$. After qubit A has been confirmed that its “spin” is up along $\mathbf{n}$, its state is projected to the eigenstate of the spin operator along $\mathbf{n}$, i.e., $|\phi\rangle = \mathbf{n} \cdot \boldsymbol{\tau}|\phi\rangle$, with $\boldsymbol{\tau} \equiv (\tau_1, \tau_2, \tau_3)$ being the Pauli matrices acting on qubit A. The state $|\phi\rangle$ is parameterized in terms of the two angles θ and φ as

$$|\phi\rangle = \cos(\theta/2)e^{-i\varphi/2}|\uparrow\rangle + \sin(\theta/2)e^{i\varphi/2}|\downarrow\rangle. \quad (19)$$

It is an elementary task to write down the projected operator $V_\phi(\tau) \equiv \langle\phi|e^{-iH\tau}|\phi\rangle$ in the following form

$$V_\phi(\tau) = c_0 + \mathbf{c} \cdot \boldsymbol{\sigma}, \quad (20)$$

where $\boldsymbol{\sigma} \equiv (\sigma_1, \sigma_2, \sigma_3)$ are Pauli matrices acting on qubit B and parameters c_0 and $\mathbf{c} \equiv (c_1, c_2, c_3)$ are complex valued. Its eigenvalues $\lambda_\pm$ and the corresponding right- and left-eigenvectors are easily found

$$\lambda_\pm = c_0 \pm c, \quad c \equiv \sqrt{\mathbf{c}^2}, \quad c_\pm \equiv c_1 \pm ic_2, \quad (21)$$

$$\begin{aligned} |u_+\rangle &= \frac{1}{\sqrt{2c(c-c_3)}} [c_-|\uparrow\rangle + (c-c_3)|\downarrow\rangle], \\ |u_-\rangle &= \frac{1}{\sqrt{2c(c-c_3)}} [(c_3-c)|\uparrow\rangle + c_+|\downarrow\rangle], \\ |v_+\rangle &= \frac{1}{\sqrt{2c(c-c_3)}} [c_+|\uparrow\rangle + (c-c_3)|\downarrow\rangle], \\ |v_-\rangle &= \frac{1}{\sqrt{2c(c-c_3)}} [(c_3-c)(\uparrow| + c_-|\downarrow|]. \end{aligned} \quad (22)$$

$$(23)$$

Now let the total Hamiltonian of this system be given by

$$\begin{aligned} H &= \frac{\omega_A}{2}(1 + \tau_3) + \frac{\omega_B}{2}(1 + \sigma_3) \\ &\quad + g(\tau_+\sigma_- + \text{h.c.}) + h(\tau_+\sigma_+ + \text{h.c.}), \end{aligned} \quad (24)$$

where real parameters g and h are responsible for the interaction between the two qubits, A and B. In this

case, the parameters $c_0, \dots, c_3$ in (20)–(23) are explicitly calculated to be

$$c_0 = \frac{1}{2} \left(\cos \frac{\tau\theta_h}{2} + \cos \frac{\tau\theta_g}{2} \right) - \frac{i}{2} \left(\frac{\omega_+}{\theta_h} \sin \frac{\tau\theta_h}{2} + \frac{\omega_-}{\theta_g} \sin \frac{\tau\theta_g}{2} \right) \cos \theta, \quad (25)$$

$$c_1 = -i \left(\frac{h}{\theta_h} \sin \frac{\tau\theta_h}{2} + \frac{g}{\theta_g} \sin \frac{\tau\theta_g}{2} \right) \sin \theta \cos \varphi, \quad (26)$$

$$c_2 = i \left(\frac{h}{\theta_h} \sin \frac{\tau\theta_h}{2} - \frac{g}{\theta_g} \sin \frac{\tau\theta_g}{2} \right) \sin \theta \sin \varphi, \quad (27)$$

$$c_3 = \frac{1}{2} \left(\cos \frac{\tau\theta_h}{2} - \cos \frac{\tau\theta_g}{2} \right) \cos \theta - \frac{i}{2} \left(\frac{\omega_+}{\theta_h} \sin \frac{\tau\theta_h}{2} - \frac{\omega_-}{\theta_g} \sin \frac{\tau\theta_g}{2} \right), \quad (28)$$

where we have introduced

$$\omega_\pm \equiv \omega_A \pm \omega_B, \quad \theta_h \equiv \sqrt{\omega_+^2 + 4h^2}, \quad \theta_g \equiv \sqrt{\omega_-^2 + 4g^2}. \quad (29)$$

In order to illustrate how an optimal purification can be achieved in this system, consider the case where we measure qubit A along the 3-direction, that is, we choose $\theta = 0$ and $|\phi\rangle = |\uparrow\rangle$. Then the eigenvalues $\lambda_\pm$ in (21) and the corresponding eigenvectors are

$$\lambda_+ = \cos \frac{\tau\theta_h}{2} - i \frac{\omega_+}{\theta_h} \sin \frac{\tau\theta_h}{2} \iff |u_+\rangle = |\uparrow\rangle, \quad (30)$$

$$\lambda_- = \cos \frac{\tau\theta_g}{2} - i \frac{\omega_-}{\theta_g} \sin \frac{\tau\theta_g}{2} \iff |u_-\rangle = |\downarrow\rangle. \quad (31)$$

Since we have

$$|\lambda_+|^2 = 1 - \frac{4h^2}{\theta_h^2} \sin^2 \frac{\tau\theta_h}{2}, \quad |\lambda_-|^2 = 1 - \frac{4g^2}{\theta_g^2} \sin^2 \frac{\tau\theta_g}{2}, \quad (32)$$

the purification can be made optimal, e.g., when the parameters are adjusted so that $h \sin(\tau\theta_h/2) = 0$ is satisfied. In this case, $|\lambda_+| = 1$ and qubit B is driven to a pure state $|\uparrow\rangle$, more quickly for larger g satisfying $\sin^2(\tau\theta_g/2) = 1$. A similar situation can happen; we can extract $|\downarrow\rangle$ in qubit B, more quickly for larger h satisfying $\sin^2(\tau\theta_h/2) = 1$, if we adjust parameters so that $g \sin(\tau\theta_g/2) = 0$ holds.

Needless to say, there are cases where such purifications are not possible. For example, consider a case where we measure qubit A in the 1-2 plane, i.e., $\theta = \pi/2$. In this case, since the parameter c_0 is real, while all the other parameters c_1, c_2 and c_3 become pure imaginary, the eigenvalues $\lambda_\pm = c_0 \pm c$ are degenerated in magnitude

$$|\lambda_+| = \sqrt{c_0^2 + |c|^2} = |\lambda_-| \quad (33)$$

and no purification can occur in this particular case.

IV. ENTANGLEMENT DISTILLATION: I

As is mentioned in the Introduction, since entanglement is one of the key elements in quantum technologies [10], it would be useful if the present scheme of purification can be used to extract an entangled state as a target pure state. Notice that since the target system has never been measured directly in the present scheme, it is considered to be suited for extraction of such a fragile pure state as an entangled state. Actually any measurement on its subsystem that consists of entanglement would result in the destruction of the entanglement.

In order to see an entanglement distillation on the basis of the present idea of purification [11, 12], we consider a total system composed of a compound system A+B, in which an entangled state is to be extracted, and another system C. Systems A and B interact with system C separately, but do not interact directly with each other. We measure system C repeatedly at regular intervals τ and endeavor to extract an entangled state as a pure state in A+B. In this section, a simple model, in which all systems A, B and C are represented by qubits, is considered with a model Hamiltonian

$$H = \frac{\Omega}{2}(1 + \sigma_3^A) + \frac{\Omega}{2}(1 + \sigma_3^B) + \frac{\omega}{2}(1 + \tau_3) \\ + g(\sigma_+^A \tau_- + \sigma_+^B \tau_- + \text{h.c.}) \\ + h(\sigma_+^A \tau_+ + \sigma_+^B \tau_+ + \text{h.c.}), \quad (34)$$

where the Pauli matrices τ_i act on system C. It is assumed here for simplicity that the two systems A and B are the same and the Hamiltonian is symmetric under the exchange A $\leftrightarrow$ B.

In order to find the spectral decomposition (10) of the projected operator $V_\phi(\tau)$ in this case, it turns out to be convenient to introduce the Bell states

$$|\Psi^\pm\rangle = \frac{1}{\sqrt{2}}[|\uparrow\downarrow\rangle \pm |\downarrow\uparrow\rangle], \quad |\Phi^\pm\rangle = \frac{1}{\sqrt{2}}[|\uparrow\uparrow\rangle \pm |\downarrow\downarrow\rangle] \quad (35)$$

as a complete orthonormal set for A+B, because we are interested in extraction of such entangled states. Indeed, the eigenstates of the total Hamiltonian H can be found after their classification according to the above mentioned A $\leftrightarrow$ B symmetry and a “parity” $\mathcal{P} \equiv \sigma_3^A \sigma_3^B \tau_3$:
1) A $\leftrightarrow$ B symmetric and $\mathcal{P} = +$

$$H \begin{pmatrix} |\Phi^+\uparrow\rangle \\ |\Phi^-\uparrow\rangle \\ |\Psi^+\downarrow\rangle \end{pmatrix} = \begin{pmatrix} \Omega + \omega & \Omega & g + h \\ \Omega & \Omega + \omega & -g + h \\ g + h & -g + h & \Omega \end{pmatrix} \begin{pmatrix} |\Phi^+\uparrow\rangle \\ |\Phi^-\uparrow\rangle \\ |\Psi^+\downarrow\rangle \end{pmatrix}, \quad (36)$$

2) A $\leftrightarrow$ B symmetric and $\mathcal{P} = -$

$$H \begin{pmatrix} |\Phi^+\downarrow\rangle \\ |\Phi^-\downarrow\rangle \\ |\Psi^+\uparrow\rangle \end{pmatrix} = \begin{pmatrix} \Omega & \Omega & g + h \\ \Omega & \Omega & g - h \\ g + h & g - h & \Omega + \omega \end{pmatrix} \begin{pmatrix} |\Phi^+\downarrow\rangle \\ |\Phi^-\downarrow\rangle \\ |\Psi^+\uparrow\rangle \end{pmatrix}, \quad (37)$$

3) A $\leftrightarrow$ B anti-symmetric and $\mathcal{P} = -$

$$H|\Psi^-\uparrow\rangle = (\Omega + \omega)|\Psi^-\uparrow\rangle, \quad (38)$$

4) A $\leftrightarrow$ B anti-symmetric and $\mathcal{P} = +$

$$H|\Psi^-\downarrow\rangle = \omega|\Psi^-\downarrow\rangle. \quad (39)$$

Here $|\Phi^+\uparrow\rangle \equiv |\Phi^+\rangle \otimes |\uparrow\rangle$, etc. Thus the time evolution operator $e^{-iH\tau}$ is expressed as

$$e^{-iH\tau} = \sum_s e^{-iE_s\tau} |s\rangle\langle s| \\ + |\Psi^-\rangle(\Psi^-| \left[e^{-i(\Omega+\omega)\tau} |\uparrow\rangle\langle\uparrow| + e^{-i\Omega\tau} |\downarrow\rangle\langle\downarrow| \right], \quad (40)$$

where the summation is taken over the six A $\leftrightarrow$ B symmetric eigenstates of H , denoted as $|s\rangle$, that are given as linear combinations of the six states in (36) and (37). Owing to the A $\leftrightarrow$ B symmetry of H , the A $\leftrightarrow$ B anti-symmetric state $|\Psi^-\rangle$ does not mix with the other (A $\leftrightarrow$ B symmetric) eigenstates.

We are now in a position to examine the spectrum of the projected operator $V_\phi(\tau) \equiv \langle\phi|e^{-iH\tau}|\phi\rangle$. If the measurement of C projects its state on

$$|\phi\rangle = \alpha|\uparrow\rangle + \beta|\downarrow\rangle, \quad (41)$$

the operator reads

$$V_\phi(\tau) = \langle\phi|e^{-iH\tau}|\phi\rangle \\ = \sum_s e^{-iE_s\tau} \left[|\alpha|^2 \langle\uparrow|s\rangle\langle s|\uparrow\rangle + |\beta|^2 \langle\downarrow|s\rangle\langle s|\downarrow\rangle \right. \\ \left. + \alpha^* \beta \langle\uparrow|s\rangle\langle s|\downarrow\rangle + \text{h.c.} \right] \\ + |\Psi^-\rangle(\Psi^-| \left[|\alpha|^2 e^{-i(\Omega+\omega)\tau} + |\beta|^2 e^{-i\Omega\tau} \right]. \quad (42)$$

From this expression, it is evident that the Bell state $|\Psi^-\rangle$ is always one of the eigenstates of this operator and if the measurement interval τ is so adjusted that the condition $\omega\tau = 2\pi$ is met, its eigenvalue λ_{Ψ^-} becomes maximum in magnitude

$$\omega\tau = 2\pi \longrightarrow |\lambda_{\Psi^-}| = 1, \quad (43)$$

irrespectively of the projected state $|\phi\rangle$ of system C because $|\alpha|^2 + |\beta|^2 = 1$. This clearly demonstrates a possibility of entanglement distillation in this simple system, in the sense that one of the conditions for optimal purification (16) can be realized by (43) and the entangled state $|\Psi^-\rangle$ would surely be extracted, only if the other eigenvalues of the operator than λ_{Ψ^-} can be made (much) smaller in magnitude. Further details of the analysis of such conditions for the entanglement distillation and its optimization are found in [11] and [12] in a slightly simplified case.

V. ENTANGLEMENT DISTILLATION: II

The example in the previous section explicitly demonstrates that we can distill an entangled state in the system A+B, through the repeated measurements on the other system C that separately interacts with A and B. The framework is rather simple and the distillation can be made optimal. There is, however, a kind of drawback in this scheme. As is clear in its exposition, it is assumed that system C, on which the measurement is performed, *always and simultaneously interacts* with both A and B and these interactions are crucial for the entanglement distillation. Stating differently, systems A and B (and C) are not (and/or will not be) able to be *separated spatially*, which implies that no entanglement between spatially separated systems is possible by the scheme presented in Sec. IV. It would not be suited to the situations where entanglements among spatially separated systems are required, as in quantum teleportation.

In this section, a resolution to this problem is presented. Since the two systems, A and B, an entanglement between which is to be driven, are considered to be placed at different places, let us consider, instead of system C which can no longer interact simultaneously with A and B, another quantum system, say X, which is assumed to interact with A and B, not simultaneously, but *successively* [13]. System X plays the role of an “entanglement mediator.” After such successive interactions with A and then B, system X is measured to confirm that it is in a certain state. If system X is found in this particular state, X is again brought to interaction with A and then with B. This process, i.e., X’s interaction with A, that with B and measurement on X, will be repeated many (N) times and we are interested in the asymptotic state of system A+B in the hope of distilling an entangled state.

There are a couple of points to be mentioned here. First, it is clear that in spite of these modifications, the new scheme presented here shares essentially the same idea of purification with the previous ones: The dynamics of the system can be affected, in an essential way, by the action of measurement, even if its effect is not direct. Second, such a successive interaction would be conveniently treated in terms of a time-dependent (effective) Hamiltonian $H(t)$. We may thus avoid possible complications caused by the introduction of spatial degrees of freedom, still keeping the essential points.

In order to see how the new scheme works, consider again a three-qubit system, A+B+X, for definiteness and simplicity. We prepare system X, say in up state $|\uparrow\rangle$, while the system A+B can be in an arbitrary mixed state. It is assumed that systems A and B are spatially separated and have no contact with each other and that only system X can interact with them locally for definite time durations. Now consider the following process:

1. System X is first brought to interaction with system A for time duration t_A . The Hamiltonian here is given by $H(t) = H_0 + H_{XA}$. Then the interaction

is switched off and the total system evolves freely with the free Hamiltonian H_0 for τ_A .

2. System X then interacts with system B for time duration t_B , the dynamics of which is now described by another Hamiltonian $H(t) = H_0 + H_{XB}$. After that, the total system again evolves freely with the Hamiltonian H_0 for τ_B .
3. A (projective) measurement is performed on system X to select only up state $|\uparrow\rangle$. Other states are discarded.

Then this process is repeated N times: $1 \rightarrow 2 \rightarrow 3 \rightarrow 1 \rightarrow \dots \rightarrow 1 \rightarrow 2 \rightarrow 3$.

It is shown below that the following choice of the Hamiltonians

$$H_0 = \frac{\omega}{2}(1 + \sigma_3^A) + \frac{\omega}{2}(1 + \sigma_3^B) + \frac{\omega}{2}(1 + \sigma_3^X),$$

$$H_{XA} = g_A \sigma_1^X \sigma_1^A, \quad H_{XB} = g_B \sigma_1^X \sigma_1^B \quad (44)$$

actually results in an entanglement distillation in system A+B. It is important to notice that the above choice of the interaction Hamiltonians is closely connected to the details of the process $1 \rightarrow 2 \rightarrow 3$ and another choice, e.g., $\sigma_+^X \sigma_-^{A(B)}$ for $H_{XA(B)}$, would result not in an entangled state, but in a product state, in this particular process.

The next task is to find the spectral decomposition of the projected operator $V_\uparrow$ defined, in this case, by

$$V_\uparrow = \langle \uparrow | e^{-iH_0\tau_B} e^{-i(H_0+H_{XB})t_B} \times e^{-iH_0\tau_A} e^{-i(H_0+H_{XA})t_A} | \uparrow \rangle. \quad (45)$$

Since a parity defined by $\mathcal{P} \equiv \sigma_3^A \sigma_3^B$ is conserved in this system, eigenstates of the operator $V_\uparrow$ are easily found. Indeed, we can classify every state of system A+B into two sectors according to the parity $\mathcal{P} = \pm$ and the action of the operator $V_\uparrow$ is closed within each sector. For $\mathcal{P} = +$ states, the action is represented by a matrix $\mathcal{M}$

$$V_\uparrow \begin{bmatrix} |\uparrow\uparrow\rangle \\ |\downarrow\downarrow\rangle \end{bmatrix} = e^{-i\omega(t_A+\tau_A+t_B+\tau_B)} \mathcal{M} \begin{bmatrix} |\uparrow\uparrow\rangle \\ |\downarrow\downarrow\rangle \end{bmatrix}, \quad (46)$$

where its matrix elements read

$$\begin{aligned} \mathcal{M}_{11} &= e^{-i\omega(t_A+2\tau_A+t_B+2\tau_B)} (\cos \zeta_A - i \sin \zeta_A \cos 2\xi_A) \\ &\quad \times (\cos \zeta_B - i \sin \zeta_B \cos 2\xi_B), \\ \mathcal{M}_{12} &= -e^{-i\omega t_A} \sin \zeta_A \sin 2\xi_A \sin g_B t_B, \\ \mathcal{M}_{21} &= -e^{-i\omega(t_B+2\tau_B)} \sin g_A t_A \sin \zeta_B \sin 2\xi_B, \\ \mathcal{M}_{22} &= \cos g_A t_A \cos g_B t_B, \end{aligned} \quad (47)$$

while, for $\mathcal{P} = -$ states, it is represented by another matrix $\mathcal{N}$

$$V_\uparrow \begin{bmatrix} |\uparrow\downarrow\rangle \\ |\downarrow\uparrow\rangle \end{bmatrix} = e^{-i\omega(t_A+t_B+2\tau_B)} \mathcal{N} \begin{bmatrix} |\uparrow\downarrow\rangle \\ |\downarrow\uparrow\rangle \end{bmatrix}, \quad (48)$$

with its matrix elements

$$\begin{aligned}\mathcal{N}_{11} &= e^{-i\omega(2\tau_A+t_B)}(\cos \zeta_A - i \sin \zeta_A \cos 2\xi_A) \cos g_B t_B, \\ \mathcal{N}_{12} &= -\sin \zeta_A \sin 2\xi_A \sin \zeta_B \sin 2\xi_B, \\ \mathcal{N}_{21} &= -e^{-i\omega(t_A+2\tau_A+t_B)} \sin g_A t_A \sin g_B t_B, \\ \mathcal{N}_{22} &= e^{-i\omega(t_A+2\tau_A)} \cos g_A t_A (\cos \zeta_B - i \sin \zeta_B \cos 2\xi_B).\end{aligned}\quad (49)$$

Here the angles are defined by

$$\zeta_{A(B)} = t_{A(B)} \sqrt{\omega^2 + g_{A(B)}^2}, \quad \tan 2\xi_{A(B)} = \frac{g_{A(B)}}{\omega}. \quad (50)$$

In order to see the possibility of entanglement distillation in this framework, it is enough to consider a much more simplified case. Let the two systems A and B be treated symmetrically, that is, all parameters are taken to be the same for A and B

$$g_A = g_B \equiv g, \quad t_A = t_B \equiv t, \quad \tau_A = \tau_B \equiv \tau, \\ (\zeta_{A(B)} \rightarrow \zeta, \quad \xi_{A(B)} \rightarrow \xi). \quad (51)$$

It is then easy to see that if the parameters satisfy

$$\cos \zeta - i \sin \zeta \cos 2\xi = -e^{i\omega\tau} \cos gt, \quad (52)$$

an optimal purification of an entangled state $|\Psi\rangle$ of the form

$$|\Psi\rangle \equiv \frac{1}{\sqrt{2}} \left[|\uparrow\downarrow\rangle + e^{i\chi} |\downarrow\uparrow\rangle \right] \quad (53)$$

with $\chi = \omega(t + \tau)$ is actually possible, provided

$$\cos gt \sin gt \neq 0, \quad \omega(t + \tau) \neq 2n\pi \quad (n: \text{integer}). \quad (54)$$

In fact, one can show that $|\Psi\rangle$ is an eigenstate of the operator $V_\uparrow$

$$V_\uparrow |\Psi\rangle = \lambda_\Psi |\Psi\rangle. \quad (55)$$

The eigenvalue λ_Ψ is maximum in magnitude

$$\lambda_\Psi = -e^{-3i\omega(t+\tau)}, \quad |\lambda_\Psi| = 1, \quad (56)$$

while all the other eigenvalues remain smaller than unity in magnitude, under the conditions (52) and (54). Therefore, we can repeat the process $1 \rightarrow 2 \rightarrow 3$ as many times as is required to achieve the desired (high) fidelity, without reducing the yield.

This is an example of (optimal) entanglement distillations, where the entanglement between two qubit systems that are (or can be) spatially separated, is extracted

through their successive interactions with another qubit, on which one and the same measurement is repeated regularly. Further details of this model and applications to other quantum systems, e.g., extraction of entanglement between two cavity modes at a distance, will be reported elsewhere.

VI. SUMMARY

In this paper, a new purification scheme recently proposed [9] is applied to a few simple qubit systems to explicitly show its ability of qubit purification (Sec. III) and entanglement distillations (Secs. IV and V) for two-qubit systems. The important and essential idea, on which these particular examples are based, is to utilize the effect caused by the action of measurement on quantum systems.

It should be stressed again that since the basic idea is so simple, that is, one has only to repeat one and the same measurement without being concerned about the preparation of a specific initial (pure) state, this purification scheme is considered to have wide applicability and flexibility. Furthermore, it enables us to make the two demands—the *maximal fidelity and non-vanishing yield*—compatible. The examples presented in this paper just show these characteristics and many variants can be devised according to the actual setups.

Acknowledgments

The authors acknowledge useful and helpful discussions with Prof. I. Ohba. Fruitful discussions with P. Facchi and S. Pascazio are also appreciated. One of the authors (H.N.) is grateful for the warm hospitality at Università di Palermo, where he enjoyed the inspiring discussions with A. Messina's group. This work is partly supported by a Grant for The 21st Century COE Program (Physics of Self-Organization Systems) at Waseda University and a Grant-in-Aid for Priority Areas Research (B) from the Ministry of Education, Culture, Sports, Science and Technology, Japan (No. 13135221), by a Grant-in-Aid for Scientific Research (C) (No. 14540280) from the Japan Society for the Promotion of Science, by a Waseda University Grant for Special Research Projects (No. 2002A-567) and by the bilateral Italian-Japanese project 15C1 on "Quantum Information and Computation" of the Italian Ministry for Foreign Affairs.

-
- [1] B. Misra and E.C.G. Sudarshan, J. Math. Phys. **18**, 756 (1977).
 - [2] T. Petrosky, S. Tasaki and I. Prigogine, Phys. Lett. A

151, 109 (1990); Physica A **170**, 306 (1991); S. Pascazio and M. Namiki, Phys. Rev. A **50**, 4582 (1994). For reviews, see, for example, H. Nakazato, M. Namiki

- and S. Pascazio, *Int. J. Mod. Phys. B* **10**, 247 (1996); D. Home and M.A.B. Whitaker, *Ann. Phys. (N.Y.)* **258**, 237 (1997); P. Facchi and S. Pascazio, in *Progress in Optics*, edited by E. Wolf (Elsevier, Amsterdam, 2001), Vol. 42, p. 147.
- [3] E.P. Wigner, *Am. J. Phys.* **31**, 6 (1963).
 - [4] W.M. Itano, D.J. Heinzen, J.J. Bollinger and D.J. Wineland, *Phys. Rev. A* **41**, 2295 (1990).
 - [5] M.C. Fischer, B. Gutiérrez-Medina and M.G. Raizen, *Phys. Rev. Lett.* **87**, 040402 (2001).
 - [6] S.R. Wilkinson, C.F. Bharucha, M.C. Fischer, K.W. Madison, P.R. Morrow, Q. Niu, B. Sundaram and M.G. Raizen, *Nature* **387**, 575 (1997).
 - [7] A.M. Lane, *Phys. Lett. A* **99**, 359 (1983); W.C. Schieve, L.P. Horwitz and J. Levitan, *Phys. Lett. A* **136**, 264 (1989); P. Facchi and S. Pascazio, *Phys. Rev. A* **62**, 023804 (2000); B. Elattari and S.A. Gurvitz, *Phys. Rev. A* **62**, 032102 (2000); A.G. Kofman and G. Kurizki, *Nature* **405**, 546 (2000); P. Facchi, H. Nakazato and S. Pascazio, *Phys. Rev. Lett.* **86**, 2699 (2001); K. Koshino and A. Shimizu, *Phys. Rev. A* **67**, 042101 (2003).
 - [8] P. Facchi, D.A. Lidar and S. Pascazio, *Phys. Rev. A*, in print (2004); P. Facchi, D.A. Lidar, H. Nakazato, S. Pascazio, S. Tasaki and A. Tokuse, in preparation.
 - [9] H. Nakazato, T. Takazawa and K. Yuasa, *Phys. Rev. Lett.* **90**, 060401 (2003); K. Yuasa, H. Nakazato and T. Takazawa, *J. Phys. Soc. Jpn.* **72** Suppl. C, 34 (2003).
 - [10] See, for example, M.A. Nielsen and I.L. Chuang, *Quantum Computation and Quantum Information* (Cambridge University Press, Cambridge, 2000); *The Physics of Quantum Information*, edited by D. Bouwmeester, A. Ekert and A. Zeilinger (Springer-Verlag, Heidelberg, 2000).
 - [11] K. Yuasa, H. Nakazato and M. Unoki, “Entanglement purification through Zeno-like measurements,” quant-ph/0402184, *J. Mod. Opt.*, in print (2004).
 - [12] H. Nakazato, M. Unoki and K. Yuasa, “Preparation and entanglement purification of qubits through Zeno-like measurements,” WU-HEP-04-01 (2004), quant-ph/0402182.
 - [13] A. Messina, *Eur. Phys. J. D* **18**, 379 (2002); D.E. Browne and M.B. Plenio, *Phys. Rev. A* **67**, 012325 (2003).